

**UNITED STATES PATENT APPLICATION**

**FOR**  
**AN OPTICAL SIGNAL RECEIVER AND METHOD WITH**  
**DECISION THRESHOLD ADJUSTMENT BASED ON**  
**A TOTAL PERCENTAGE ERROR INDICATOR**

**BY**

**Steve W. Cornelius**

09516337 072701

**Certification Under 37 C.F.R. Section 1.10**

I hereby certify that this New Application Transmittal Letter and the documents referred to as being enclosed therein are being deposited with the United States Postal Service on this 27<sup>th</sup> day of July, 2001 in an envelope marked as "Express Mail Post Office to Addressee" Mail Label Number EL589573010US addressed to Box Patent Application, Commissioner of Patents and Trademarks, Washington, D.C. 20231.

Carol S. Parker/Hines

(signature of person mailing paper)

**AN OPTICAL SIGNAL RECEIVER AND METHOD WITH DECISION  
THRESHOLD ADJUSTMENT BASED ON A TOTAL PERCENTAGE  
ERROR INDICATOR FIELD OF THE INVENTION**

5           The present invention relates in general to receivers and methods of receiving for communication systems and, in particular, to an optical signal receiver and optical signal receiving method including decision threshold adjustment.

**BACKGROUND OF THE INVENTION**

10           It is well known than signals transported over optical communication networks suffer degradation between associated transmitters and receivers. Signal degradation may result from a variety of system parameters including the total transmission distance, the transmission fiber type, the number of optical amplifications to a signal, the number of system channels, etc.

Optical networks are, however, being developed with ever-increasing signal transmission speeds and distances. Channel counts have also been increasing in wavelength division multiplexed transmission systems. The greater transmission distances, speeds and higher channel counts directly effect received signal quality.

To maintain high fidelity signal reception in optical networks, advances in receiver design have been proposed. For example, receivers are constructed with the goal of achieving an acceptable BER (bit error rate), which is the ratio of the number of incorrectly received bits to the total number of received bits. Typically, this is achieved by adjusting and fixing the decision threshold of a comparator within the receiver while providing a well-known optical test signal at the comparator data input. The decision threshold is a reference voltage against which the strength of a received signal is compared. If the received signal is above the decision threshold,

it is interpreted as being “on”, but if the received signal is below the decision threshold, it is interpreted as being “off”.

It is also known that a decision threshold may be established from the eye diagram of the received signal. An exemplary eye diagram is illustrated in FIG.1a.

5 In general, an eye diagram may be observed on an oscilloscope by monitoring the receiver data output voltage on the vertical input of the oscilloscope and triggering on the data clock. Key features of an eye diagram, as illustrated in Fig. 1a, include the crossing points C1, C2, useable eye width (i.e. the time distance on the horizontal scale between points C1 and C2) and usable eye height H (voltage).

10 In an ideal received signal such as the one shown in Fig. 1a, the crossing points C1,C2 would be centered and symmetrical, and the open area would be as large as possible, indicating strong pulse width and height in the received signal. A decision threshold DT may be selected to correspond with the voltage level at the crossing points C1, C2, as shown. In contrast, a non-ideal received signal may have an eye diagram like the one shown in Fig. 1b in which the eye is not open and the crossing points are not centered or symmetric.

15 A difficulty with such receiver designs, however, is that the eye diagram itself depends on all of the above-mentioned parameters that effect signal quality. All these parameters can change with time, e.g. due to system upgrades to add more channels, changes in fiber plant, or changes in optical amplifier performance. Such changes can alter the received “eye diagram”  
20 such as in the eye diagram shown in Fig. 1b, leading to a degradation of the BER in the absence of a re-optimized decision threshold.

In an attempt to minimize the adverse effects of system changes, error correction schemes such as forward error correction (FEC) have been incorporated into receiver designs. FEC

generally includes generation of a control code at the transmission site. The control code is transmitted with the data to a receiver. Error correction may be achieved based on various algorithms that compensate for specific detected errors in the control code. Although FEC schemes have achieved wide acceptance, there is room for improvement in basic receiver design  
5 that addresses the underlying BER variation resulting from changes in system parameters.

Accordingly, there is a need in the art for optical receiver configuration and/or optical signal control method that adjusts the receiver decision threshold to reduce the BER.

## SUMMARY OF THE INVENTION

The present invention is organized about the concept of providing an optical receiver configuration and a method of controlling an optical signal receiver that adjusts a decision threshold that reduces the BER.

The receiver includes a comparator having a data input and a digital data output. An error correction and detection circuit provides an error calculation signal representative of errors in the data output from the comparator. Based on the error calculation signal, a control circuit modifies the comparator decision threshold and, preferably, a rate of comparison threshold adjustment to reduce the BER of the receiver.

In particular, an optical receiver consistent with the invention may include a comparator for receiving an input data signal from an optical-to-electrical signal converter and a decision  
20 threshold signal and providing a digital output data signal; an error detection and correction circuit for receiving the digital output data signal, detecting errors in the digital output data signal and correcting detected errors in the digital output data signal; the error detection and correction circuit also providing an error signal representative of a number of corrected "1"s and number of

corrected "0"s in the output data signal; and a control circuit for receiving the error signal, calculating a total percentage error indicator based on the error signal and adjusting the decision threshold signal in response to the total percentage error indicator.

In addition, the control circuit may change a rate of the decision threshold adjustment  
5 based on the total percentage error indicator.

Another optical receiver consistent with the invention may include a photodetector optically coupled to a fiber optic network: the photodetector converting an optical signal received from the fiber optic network to an electrical input data signal; a comparator operatively coupled to the photodetector and to a decision threshold input port; the comparator comparing the electrical input data signal to a decision threshold signal to provide a digital output data signal; an error detection and correction circuit operatively coupled to the comparator; the error detection and correction circuit detecting errors in the digital output data signal and correcting detected errors in the digital output data signal; the error detection and correction circuit also providing an error signal representative of a number of corrected "1"s and number of corrected "0"s in the output data signal; and a control circuit operatively coupled to the error detection and correction circuit and to the decision threshold input port of the comparator, the control circuit calculating a total percentage error indicator based on the error signal and adjusting the decision threshold signal in response to the total percentage error indicator.

In addition, the control circuit may change a rate of the decision threshold adjustment  
20 based on the total percentage error indicator.

The control circuit may also include a microprocessor circuit for receiving the error signal and a digital to analog converter for providing the decision threshold signal, the

microprocessor circuit providing a digital control signal to the digital to analog converter for controlling the decision threshold signal.

The error detection and correction circuit may include an FEC circuit and preferably outputs an error signal that may, for example, be representative the total number of "1"s and total number of "0"s corrected by the error detection and correction circuit.

The receiver may also include a clock and data recovery circuit for receiving the output data signal and providing the data output signal and a data input clock to the error detection circuit, and a photodiode may be provided whereby the data input signal is representative an optical data signal imparted on the photodiode.

An optical receiving method consistent with the invention may reduce bit errors in a digital data output signal output from an optical receiver having a comparator comparing an input data signal from an optical-to-electrical signal converter to a decision threshold signal to provide the digital output data signal, the method comprising: inputting a number of corrected "1"s and a number of corrected "0"s corrected in the output data signal; calculating a total percentage error indicator based on the number of corrected "1"s and the number of corrected "0"s in the output data signal; and adjusting the decision threshold signal in response to the calculated total percentage error indicator.

Moreover, the method may also change a rate of the decision threshold adjustment based on the calculated total percentage error indicator.

Alternatively, the method may change the decision threshold by a stepsize amount in response to the calculated total percentage error indicator.

In another alternative, the method may change the decision threshold by a stepsize amount related to the calculated total percentage error indicator.

### BRIEF DESCRIPTION OF THE DRAWING

For a better understanding of the present invention, together with other objects, features  
5 and advantages, reference should be made to the following detailed description which should be  
read in conjunction with the following figures wherein like numerals represent like parts:

FIG. 1a: is an exemplary and conventional optical signal eye-diagram of a high-quality  
signal;

FIG. 1b: is an exemplary and conventional optical signal eye-diagram of a low-quality  
signal;

FIG. 2: is a block diagram of an exemplary receiver consistent with a first construction of  
the invention;

FIG. 3: is a block diagram of an exemplary receiver consistent with a second construction  
of the invention;

FIG. 4: is a block diagram of an exemplary receiver consistent with a third construction of  
the invention;

FIG. 5: is a flow chart illustrating a receiver searching operation consistent with the  
invention that may be performed by the exemplary receivers;

FIG. 6: is a flow chart illustrating a receiver threshold tuning operation consistent with the  
invention that may be performed by the exemplary receivers;

FIG. 7: is a flow chart illustrating an alternative receiver threshold tuning operation  
consistent with the invention that may be performed by the exemplary receivers;

- FIG. 8a: is a flow chart illustrating another alternative receiver threshold tuning operation consistent with the invention that may be performed by the exemplary receivers;
- FIG. 8b: is a flow chart illustrating yet another alternative receiver threshold tuning operation consistent with the invention that may be performed by the exemplary receivers;
- FIG. 9 : is a plot of an exemplary percentage error indicator (difference/total) vs. DAC output that illustrates aspects of the invention; and
- FIG. 10: is a chart of test data including DAC count, ones, zeroes, total errors, and difference/total that further illustrates aspects of the invention.

## DETAILED DESCRIPTION OF THE INVENTION

The following detailed description of the invention refers to the accompanying drawings. The same reference numbers in different drawings identify the same or similar elements. Also, the following detailed description does not limit the invention. Instead, the scope of the invention is defined by the appended claims and equivalents thereof.

The expression "optically communicates" as used herein refers to any connection, coupling, link or the like by which optical signals carried by one optical system element are imparted to the "communicating" element. Such "optically communicating" devices are not necessarily directly connected to one another and may be separated by intermediate optical components or devices. Likewise, the expressions "coupled", "connection" and "operative connection" as used herein are relative terms and do not require a direct physical connection.

FIG. 2 illustrates an exemplary embodiment of a receiver circuit 1 consistent with the invention. The receiver circuit 1 is typically installed in a fiber optic system 90 as shown but it may



also be located in a variety of other configurations. The fiber optic system 90 illustrated in Fig. 1 includes a fiber optic transmitter 5 that sends an optical signal to a photodetector 12 via a fiber optic network 10. The transmitter 5, fiber optic network 10 and photodetector 12 are conventional elements that may be constructed in a variety of manners as is known in the art.

5 The type of transmission modulation utilized by the transmitter 5 is not limited by the invention as the modulation is independent of error coding. For example, the invention may use “on”/“off” keying (OOK) for modulation whereby an optical pulse is transmitted in the “on” state - signaling a logical “1” - and the absence of the pulse corresponds to the “off” state – signaling a logical zero. Other modulation formats include RZ (return-to-zero), NRZ (non-return-to-zero), soliton, QAM (quadrature amplitude modulation) and QPSK (quadratic phase shift modulation).

10 15 20 25 30 35 40 45 50 55 60 65 70 75 80 85 90 95 100 105 110 115 120 125 130 135 140 145 150 155 160 165 170 175 180 185 190 195 200 205 210 215 220 225 230 235 240 245 250 255 260 265 270 275 280 285 290 295 300 305 310 315 320 325 330 335 340 345 350 355 360 365 370 375 380 385 390 395 400 405 410 415 420 425 430 435 440 445 450 455 460 465 470 475 480 485 490 495 500 505 510 515 520 525 530 535 540 545 550 555 560 565 570 575 580 585 590 595 600 605 610 615 620 625 630 635 640 645 650 655 660 665 670 675 680 685 690 695 700 705 710 715 720 725 730 735 740 745 750 755 760 765 770 775 780 785 790 795 800 805 810 815 820 825 830 835 840 845 850 855 860 865 870 875 880 885 890 895 900 905 910 915 920 925 930 935 940 945 950 955 960 965 970 975 980 985 990 995 1000

The optical signal from transmitter 5 is received by photodetector 12 and converted thereby into an analog electrical signal. Of course, other elements may be used in place of or in conjunction with photodetector 12 to perform this O/E (optical-to-electrical) signal conversion. One example is the conventional limiting amplifier 14 which is an optional component whose intended purpose is to amplify and limit the signal from the photodiode 12 to a level that is appropriate for coupling to the receiver circuit 1 components.

As shown, the receiver circuit 1 may include a comparator 16 coupled to the output of the limiting amplifier 14; a clock and data recovery (CDR) circuit 18 coupled to the output of the comparator 16; an error detection & correction circuit 20 coupled to the output of the CDR circuit; and a control circuit 22 coupled to an error calculation output of the error detection & correction circuit 20.

In general, the control circuit 22 provides a decision threshold signal to the comparator 16

on line 44 and may dynamically adjust the decision threshold to reduce the BER in the receiver circuit 1 output, e.g. the output of the error detection & correction circuit 20 on line 46.

Although the illustrated embodiment includes particular circuit elements, those skilled in the art will recognize that a receiver consistent with the invention may have a variety of configurations.

5 For example, the CDR circuit 18 and/or the limiting amplifier 14 may be omitted or replaced by other elements in a particular receiver. It is to be understood, therefore, that the illustrated exemplary embodiment is provided only by way of illustration, not of limitation.

With continued reference to FIG. 2, in a manner well known to those skilled in the art, the photodiode 12 converts an optical signal imparted thereon into an analog electrical signal on line 26. The conventional limiting amplifier 14 amplifies and limits the signal from the photodiode to a level that is appropriate for coupling to the remainder of the receiver circuit 1 components. The analog output of the amplifier 14 is coupled to the data input of the comparator 16.

10  
15  
20  
25  
30  
35  
40  
45  
50  
55  
60  
65  
70  
75  
80  
85  
90  
95  
100  
105  
110  
115  
120  
125  
130  
135  
140  
145  
150  
155  
160  
165  
170  
175  
180  
185  
190  
195  
200  
205  
210  
215  
220  
225  
230  
235  
240  
245  
250  
255  
260  
265  
270  
275  
280  
285  
290  
295  
300  
305  
310  
315  
320  
325  
330  
335  
340  
345  
350  
355  
360  
365  
370  
375  
380  
385  
390  
395  
400  
405  
410  
415  
420  
425  
430  
435  
440  
445  
450  
455  
460  
465  
470  
475  
480  
485  
490  
495  
500  
505  
510  
515  
520  
525  
530  
535  
540  
545  
550  
555  
560  
565  
570  
575  
580  
585  
590  
595  
600  
605  
610  
615  
620  
625  
630  
635  
640  
645  
650  
655  
660  
665  
670  
675  
680  
685  
690  
695  
700  
705  
710  
715  
720  
725  
730  
735  
740  
745  
750  
755  
760  
765  
770  
775  
780  
785  
790  
795  
800  
805  
810  
815  
820  
825  
830  
835  
840  
845  
850  
855  
860  
865  
870  
875  
880  
885  
890  
895  
900  
905  
910  
915  
920  
925  
930  
935  
940  
945  
950  
955  
960  
965  
970  
975  
980  
985  
990  
995  
1000  
1005  
1010  
1015  
1020  
1025  
1030  
1035  
1040  
1045  
1050  
1055  
1060  
1065  
1070  
1075  
1080  
1085  
1090  
1095  
1100  
1105  
1110  
1115  
1120  
1125  
1130  
1135  
1140  
1145  
1150  
1155  
1160  
1165  
1170  
1175  
1180  
1185  
1190  
1195  
1200  
1205  
1210  
1215  
1220  
1225  
1230  
1235  
1240  
1245  
1250  
1255  
1260  
1265  
1270  
1275  
1280  
1285  
1290  
1295  
1300  
1305  
1310  
1315  
1320  
1325  
1330  
1335  
1340  
1345  
1350  
1355  
1360  
1365  
1370  
1375  
1380  
1385  
1390  
1395  
1400  
1405  
1410  
1415  
1420  
1425  
1430  
1435  
1440  
1445  
1450  
1455  
1460  
1465  
1470  
1475  
1480  
1485  
1490  
1495  
1500  
1505  
1510  
1515  
1520  
1525  
1530  
1535  
1540  
1545  
1550  
1555  
1560  
1565  
1570  
1575  
1580  
1585  
1590  
1595  
1600  
1605  
1610  
1615  
1620  
1625  
1630  
1635  
1640  
1645  
1650  
1655  
1660  
1665  
1670  
1675  
1680  
1685  
1690  
1695  
1700  
1705  
1710  
1715  
1720  
1725  
1730  
1735  
1740  
1745  
1750  
1755  
1760  
1765  
1770  
1775  
1780  
1785  
1790  
1795  
1800  
1805  
1810  
1815  
1820  
1825  
1830  
1835  
1840  
1845  
1850  
1855  
1860  
1865  
1870  
1875  
1880  
1885  
1890  
1895  
1900  
1905  
1910  
1915  
1920  
1925  
1930  
1935  
1940  
1945  
1950  
1955  
1960  
1965  
1970  
1975  
1980  
1985  
1990  
1995  
2000  
2005  
2010  
2015  
2020  
2025  
2030  
2035  
2040  
2045  
2050  
2055  
2060  
2065  
2070  
2075  
2080  
2085  
2090  
2095  
2100  
2105  
2110  
2115  
2120  
2125  
2130  
2135  
2140  
2145  
2150  
2155  
2160  
2165  
2170  
2175  
2180  
2185  
2190  
2195  
2200  
2205  
2210  
2215  
2220  
2225  
2230  
2235  
2240  
2245  
2250  
2255  
2260  
2265  
2270  
2275  
2280  
2285  
2290  
2295  
2300  
2305  
2310  
2315  
2320  
2325  
2330  
2335  
2340  
2345  
2350  
2355  
2360  
2365  
2370  
2375  
2380  
2385  
2390  
2395  
2400  
2405  
2410  
2415  
2420  
2425  
2430  
2435  
2440  
2445  
2450  
2455  
2460  
2465  
2470  
2475  
2480  
2485  
2490  
2495  
2500  
2505  
2510  
2515  
2520  
2525  
2530  
2535  
2540  
2545  
2550  
2555  
2560  
2565  
2570  
2575  
2580  
2585  
2590  
2595  
2600  
2605  
2610  
2615  
2620  
2625  
2630  
2635  
2640  
2645  
2650  
2655  
2660  
2665  
2670  
2675  
2680  
2685  
2690  
2695  
2700  
2705  
2710  
2715  
2720  
2725  
2730  
2735  
2740  
2745  
2750  
2755  
2760  
2765  
2770  
2775  
2780  
2785  
2790  
2795  
2800  
2805  
2810  
2815  
2820  
2825  
2830  
2835  
2840  
2845  
2850  
2855  
2860  
2865  
2870  
2875  
2880  
2885  
2890  
2895  
2900  
2905  
2910  
2915  
2920  
2925  
2930  
2935  
2940  
2945  
2950  
2955  
2960  
2965  
2970  
2975  
2980  
2985  
2990  
2995  
3000  
3005  
3010  
3015  
3020  
3025  
3030  
3035  
3040  
3045  
3050  
3055  
3060  
3065  
3070  
3075  
3080  
3085  
3090  
3095  
3100  
3105  
3110  
3115  
3120  
3125  
3130  
3135  
3140  
3145  
3150  
3155  
3160  
3165  
3170  
3175  
3180  
3185  
3190  
3195  
3200  
3205  
3210  
3215  
3220  
3225  
3230  
3235  
3240  
3245  
3250  
3255  
3260  
3265  
3270  
3275  
3280  
3285  
3290  
3295  
3300  
3305  
3310  
3315  
3320  
3325  
3330  
3335  
3340  
3345  
3350  
3355  
3360  
3365  
3370  
3375  
3380  
3385  
3390  
3395  
3400  
3405  
3410  
3415  
3420  
3425  
3430  
3435  
3440  
3445  
3450  
3455  
3460  
3465  
3470  
3475  
3480  
3485  
3490  
3495  
3500  
3505  
3510  
3515  
3520  
3525  
3530  
3535  
3540  
3545  
3550  
3555  
3560  
3565  
3570  
3575  
3580  
3585  
3590  
3595  
3600  
3605  
3610  
3615  
3620  
3625  
3630  
3635  
3640  
3645  
3650  
3655  
3660  
3665  
3670  
3675  
3680  
3685  
3690  
3695  
3700  
3705  
3710  
3715  
3720  
3725  
3730  
3735  
3740  
3745  
3750  
3755  
3760  
3765  
3770  
3775  
3780  
3785  
3790  
3795  
3800  
3805  
3810  
3815  
3820  
3825  
3830  
3835  
3840  
3845  
3850  
3855  
3860  
3865  
3870  
3875  
3880  
3885  
3890  
3895  
3900  
3905  
3910  
3915  
3920  
3925  
3930  
3935  
3940  
3945  
3950  
3955  
3960  
3965  
3970  
3975  
3980  
3985  
3990  
3995  
4000  
4005  
4010  
4015  
4020  
4025  
4030  
4035  
4040  
4045  
4050  
4055  
4060  
4065  
4070  
4075  
4080  
4085  
4090  
4095  
4100  
4105  
4110  
4115  
4120  
4125  
4130  
4135  
4140  
4145  
4150  
4155  
4160  
4165  
4170  
4175  
4180  
4185  
4190  
4195  
4200  
4205  
4210  
4215  
4220  
4225  
4230  
4235  
4240  
4245  
4250  
4255  
4260  
4265  
4270  
4275  
4280  
4285  
4290  
4295  
4300  
4305  
4310  
4315  
4320  
4325  
4330  
4335  
4340  
4345  
4350  
4355  
4360  
4365  
4370  
4375  
4380  
4385  
4390  
4395  
4400  
4405  
4410  
4415  
4420  
4425  
4430  
4435  
4440  
4445  
4450  
4455  
4460  
4465  
4470  
4475  
4480  
4485  
4490  
4495  
4500  
4505  
4510  
4515  
4520  
4525  
4530  
4535  
4540  
4545  
4550  
4555  
4560  
4565  
4570  
4575  
4580  
4585  
4590  
4595  
4600  
4605  
4610  
4615  
4620  
4625  
4630  
4635  
4640  
4645  
4650  
4655  
4660  
4665  
4670  
4675  
4680  
4685  
4690  
4695  
4700  
4705  
4710  
4715  
4720  
4725  
4730  
4735  
4740  
4745  
4750  
4755  
4760  
4765  
4770  
4775  
4780  
4785  
4790  
4795  
4800  
4805  
4810  
4815  
4820  
4825  
4830  
4835  
4840  
4845  
4850  
4855  
4860  
4865  
4870  
4875  
4880  
4885  
4890  
4895  
4900  
4905  
4910  
4915  
4920  
4925  
4930  
4935  
4940  
4945  
4950  
4955  
4960  
4965  
4970  
4975  
4980  
4985  
4990  
4995  
5000  
5005  
5010  
5015  
5020  
5025  
5030  
5035  
5040  
5045  
5050  
5055  
5060  
5065  
5070  
5075  
5080  
5085  
5090  
5095  
5100  
5105  
5110  
5115  
5120  
5125  
5130  
5135  
5140  
5145  
5150  
5155  
5160  
5165  
5170  
5175  
5180  
5185  
5190  
5195  
5200  
5205  
5210  
5215  
5220  
5225  
5230  
5235  
5240  
5245  
5250  
5255  
5260  
5265  
5270  
5275  
5280  
5285  
5290  
5295  
5300  
5305  
5310  
5315  
5320  
5325  
5330  
5335  
5340  
5345  
5350  
5355  
5360  
5365  
5370  
5375  
5380  
5385  
5390  
5395  
5400  
5405  
5410  
5415  
5420  
5425  
5430  
5435  
5440  
5445  
5450  
5455  
5460  
5465  
5470  
5475  
5480  
5485  
5490  
5495  
5500  
5505  
5510  
5515  
5520  
5525  
5530  
5535  
5540  
5545  
5550  
5555  
5560  
5565  
5570  
5575  
5580  
5585  
5590  
5595  
5600  
5605  
5610  
5615  
5620  
5625  
5630  
5635  
5640  
5645  
5650  
5655  
5660  
5665  
5670  
5675  
5680  
5685  
5690  
5695  
5700  
5705  
5710  
5715  
5720  
5725  
5730  
5735  
5740  
5745  
5750  
5755  
5760  
5765  
5770  
5775  
5780  
5785  
5790  
5795  
5800  
5805  
5810  
5815  
5820  
5825  
5830  
5835  
5840  
5845  
5850  
5855  
5860  
5865  
5870  
5875  
5880  
5885  
5890  
5895  
5900  
5905  
5910  
5915  
5920  
5925  
5930  
5935  
5940  
5945  
5950  
5955  
5960  
5965  
5970  
5975  
5980  
5985  
5990  
5995  
6000  
6005  
6010  
6015  
6020  
6025  
6030  
6035  
6040  
6045  
6050  
6055  
6060  
6065  
6070  
6075  
6080  
6085  
6090  
6095  
6100  
6105  
6110  
6115  
6120  
6125  
6130  
6135  
6140  
6145  
6150  
6155  
6160  
6165  
6170  
6175  
6180  
6185  
6190  
6195  
6200  
6205  
6210  
6215  
6220  
6225  
6230  
6235  
6240  
6245  
6250  
6255  
6260  
6265  
6270  
6275  
6280  
6285  
6290  
6295  
6300  
6305  
6310  
6315  
6320  
6325  
6330  
6335  
6340  
6345  
6350  
6355  
6360  
6365  
6370  
6375  
6380  
6385  
6390  
6395  
6400  
6405  
6410  
6415  
6420  
6425  
6430  
6435  
6440  
6445  
6450  
6455  
6460  
6465  
6470  
6475  
6480  
6485  
6490  
6495  
6500  
6505  
6510  
6515  
6520  
6525  
6530  
6535  
6540  
6545  
6550  
6555  
6560  
6565  
6570  
6575  
6580  
6585  
6590  
6595  
6600  
6605  
6610  
6615  
6620  
6625  
6630  
6635  
6640  
6645  
6650  
6655  
6660  
6665  
6670  
6675  
6680  
6685  
6690  
6695  
6700  
6705  
6710  
6715  
6720  
6725  
6730  
6735  
6740  
6745  
6750  
6755  
6760  
6765  
6770  
6775  
6780  
6785  
6790  
6795  
6800  
6805  
6810  
6815  
6820  
6825  
6830  
6835  
6840  
6845  
6850  
6855  
6860  
6865  
6870  
6875  
6880  
6885  
6890  
6895  
6900  
6905  
6910  
6915  
6920  
6925  
6930  
6935  
6940  
6945  
6950  
6955  
6960  
6965  
6970  
6975  
6980  
6985  
6990  
6995  
7000  
7005  
7010  
7015  
7020  
7025  
7030  
7035  
7040  
7045  
7050  
7055  
7060  
7065  
7070  
7075  
7080  
7085  
7090  
7095  
7100  
7105  
7110  
7115  
7120  
7125  
7130  
7135  
7140  
7145  
7150  
7155  
7160  
7165  
7170  
7175  
7180  
7185  
7190  
7195  
7200  
7205  
7210  
7215  
7220  
7225  
7230  
7235  
7240  
7245  
7250  
7255  
7260  
7265  
7270  
7275  
7280  
7285  
7290  
7295  
7300  
7305  
7310  
7315  
7320  
7325  
7330  
7335  
7340  
7345  
7350  
7355  
7360  
7365  
7370  
7375  
7380  
7385  
7390  
7395  
7400  
7405  
7410  
7415  
7420  
7425  
7430  
7435  
7440  
7445  
7450  
7455  
7460  
7465  
7470  
7475  
7480  
7485  
7490  
7495  
7500  
7505  
7510  
7515  
7520  
7525  
7530  
7535  
7540  
7545  
7550  
7555  
7560  
7565  
7570  
7575  
7580  
7585  
7590  
7595  
7600  
7605  
7610  
7615  
7620  
7625  
7630  
7635  
7640  
7645  
7650  
7655  
7660  
7665  
7670  
7675  
7680  
7685  
7690  
7695  
7700  
7705  
7710  
7715  
7720  
7725  
7730  
7735  
7740  
7745  
7750  
7755  
7760  
7765  
7770  
7775  
7780  
7785  
7790  
7795  
7800  
7805  
7810  
7815  
7820  
7825  
7830  
7835  
7840  
7845  
7850  
7855  
7860  
7865  
7870  
7875  
7880  
7885  
7890  
7895  
7900  
7905  
7910  
7915  
7920  
7925  
7930  
7935  
7940  
7945  
7950  
7955  
7960  
7965  
7970  
7975  
7980  
7985  
7990  
7995  
8000  
8005  
8010  
8015  
8020  
8025  
8030  
8035  
8040  
8045  
8050  
8055  
8060  
8065  
8070  
8075  
8080  
8085  
8090  
8095  
8100  
8105  
8110  
8115  
8120  
8125  
8130  
8135  
8140  
8145  
8150  
8155  
8160  
8165  
8170  
8175  
8180  
8185  
8190  
8195  
8200  
8205  
8210  
8215  
8220  
8225  
8230  
8235  
8240  
8245  
8250  
8255  
8260  
8265  
8270  
8275  
8280  
8285  
8290  
8295  
8300  
8305  
8310  
8315  
8320  
8325  
8330  
8335  
8340  
8345  
8350  
8355  
8360  
8365  
8370  
8375  
8380  
8385  
8390  
8395  
8400  
8405  
8410  
8415  
8420  
8425  
8430  
8435  
8440  
8445  
8450  
8455  
8460  
8465  
8470  
8475  
8480  
8485  
8490  
8495  
8500  
8505  
8510  
8515  
8520  
8525  
8530  
8535  
8540  
8545  
8550  
8555  
8560  
8565  
8570  
8575  
8580  
8585  
8590  
8595  
8600  
8605  
8610  
8615  
8620  
8625  
8630  
8635  
8640  
8645  
8650  
8655  
8660  
8665  
8670  
8675  
8680  
8685  
8690  
8695  
8700  
8705  
8710  
8715  
8720  
8725  
8730  
8735  
8740  
8745  
8750  
8755  
8760  
8765  
8770  
8775  
8780  
8785  
8790  
8795  
8800  
8805  
8810  
8815  
8820  
8825  
8830  
8835  
8840  
8845  
8850  
8855  
8860  
8865  
8870  
8875  
8880  
8885  
8890  
8895  
8900  
8905  
8910  
8915  
8920  
8925  
8930  
8935  
8940  
8945  
8950  
8955  
8960  
8965  
8970  
8975  
8980  
8985  
8990  
8995  
9000  
9005  
9010  
9015  
9020  
9025  
9030  
9035  
9040  
9045  
9050  
9055  
9060  
9065  
9070  
9075  
9080  
9085  
9090  
9095  
9100  
9105  
9110  
9115  
9120  
9125  
9130  
9135  
9140  
9145  
9150  
9155  
9160  
9165  
9170  
9175  
9180  
9185  
9190  
9195  
9200  
9205  
9210  
9215  
9220  
9225  
9230  
9235  
9240  
9245  
9250  
9255  
9260  
9265  
9270  
9275  
9280  
9285  
9290  
9295  
9300  
9305  
9310  
9315  
9320  
9325  
9330  
9335  
9340  
9345  
9350  
9355  
9360  
9365  
9370  
9375  
9380  
9385  
9390  
9395  
9400  
9405  
9410  
9415  
9420  
9425  
9430  
9435  
9440  
9445  
9450  
9455  
9460  
9465  
9470  
9475  
9480  
9485  
9490  
9495  
9500  
9505  
9510  
9515  
9520  
9525  
9530  
9535  
9540  
9545  
9550  
9555  
9560  
9565  
9570  
9575  
9580  
9585  
9590  
9595  
9600  
9605  
9610  
9615  
9620  
9625  
9630  
9635  
9640  
9645  
9650  
9655  
9660  
9665  
9670  
9675  
9680  
9685  
9690  
9695  
9700  
9705  
9710  
9715  
9720  
9725  
9730  
9735  
9740  
9745  
9750  
9755  
9760  
9765  
9770  
9775  
9780  
9785  
9790  
9795  
9800  
9805  
9810  
9815  
9820  
9825  
9830  
9835  
9840  
9845  
9850  
9855  
9860  
9865  
9870  
9875  
9880  
9885  
9890  
9895  
9900  
9905  
9910  
9915  
9920  
9925  
9930  
9935  
9940  
9945  
9950  
9955  
9960  
9965  
9970  
9975  
9980  
9985  
9990  
9995  
10000  
10005  
10010  
10015  
10020  
10025  
10030  
10035  
10040  
10045  
10050  
10055  
10060  
10065  
10070  
10075  
10080  
10085  
10090  
10095  
10100  
10105  
10110  
10115  
10120  
101

be accomplished in a variety of ways, e.g. using a phase locked loop, saw filter, etc. Also, the CDR circuit 18 could be omitted from an embodiment consistent with the invention if its output is not required by the error detection & correction circuit 20.

In the illustrated embodiment, the clock and data are provided on separate outputs 32,34 of the CDR 18 and are coupled to the error detection & correction circuit 20. The error detection & correction circuit 20 provides an error signal on line 36. The error signal is representative of the number of errors received in the input data stream, and may be provided in a variety of forms, e.g. total number of received errors, numbers of corrected bits, etc but should preferably convey the number of corrected "1"s and the number of corrected "0"s. The error detection circuit 20 provides a corrected data output on line 46.

A variety of configurations for the error detection & correction circuit 20 will be apparent to those skilled in the art. For example, the error signal can be provided by FEC-type circuitry, which, as discussed above, provides error correction based on predefined algorithms. In this case, a corrected data output would be provided on line 46. The corrected data output would be derived from the particular FEC algorithm used, and would include a number "1"s corrected from "0"s in the input, and a number of "0"s corrected from "1"s in the input.

In a configuration where an FEC circuit is not necessary or desired, those skilled in the art will recognize other configurations of error detection & correction circuits. For example, data stream errors can be obtained from other error detection or error correction codes. If a data header and payload format is used such as in SONET or SDH, it is preferable to use coding that is outside of the payload in order to obtain a sense of directionality for the decision threshold change over multiple frames.

The error signal from the error detection & correction circuit 20 is coupled to the control circuit 22, which provides a decision threshold to the comparator 16 on line 44 based on or in response to the error signal.

In the illustrated exemplary embodiment shown in Fig. 2, the error signal on line 36 is coupled to an input of a microprocessor circuit 38. The microprocessor 38 performs some calculations and provides a digital output on line 40 to a conventional digital to analog converter 42 (DAC) for modifying the analog output of the DAC, which is provided as the comparator decision threshold on line 44.

The microprocessor circuit 38 may be constructed from, for example, a general purpose microprocessor, an application specific integrated circuit (ASIC), a field programmable gate array (FPGA), etc.

The analog output of the DAC 42 is increased or decreased by a corresponding increase or decrease in the number of DAC points (counts) provided from the processor 38 to the DAC 42 on line 40. A DAC point is, therefore, the digital input to the DAC 42 required to make a corresponding known change in the DAC analog output on line 26. For example, a one DAC point increase or decrease of the microprocessor output to the DAC may result in a corresponding increase or decrease of the DAC analog output by one millivolt. By modifying the digital input to the DAC 42 based on the error signal, the microprocessor 38 adjusts the output of the DAC 42 in a direction (i.e. either increasing or decreasing) to reduce the total number of errors in the receiver output data stream 46.

Of course, if the comparator 16 were capable of receiving a digital threshold signal then the DAC 42 could be eliminated and the microprocessor circuit 38 could directly output a digital

threshold signal to the comparator 16. Moreover, the DAC may be included within the comparator 16 rather than within the control circuit 22.

Figure 3 illustrates another alternative construction of the invention. Generally speaking, the DAC 42 of Fig. 2 may be replaced with a potentiometer 43 as shown in Fig. 3. In other words, control circuit 23 may include a microprocessor circuit 38 and a potentiometer coupled to the microprocessor 38. The potentiometer 43 may receive a control signal from the microprocessor. This control signal would adjust the potentiometer 43 and, thereby, the threshold signal voltage supplied to the comparator 16.

Figure 4 illustrates yet another alternative construction. Generally speaking, a pulse-width modulated signal 40 may be used as the threshold signal in receiver circuit 3. More specifically, the microprocessor circuit 38 in control circuit 24 may output a pulse-width modulated signal 40 as the threshold signal and vary the width of the pulse to change the threshold. Instead of varying the pulse width of signal 40, the duty cycle and/or pulse height may be varied. An RC circuit including, for example, the resistor 52 and capacitor 54 shown in Figure 4 may be used to condition the signal 40 before it is supplied as a threshold signal to the comparator 16.

## Operation

Many devices used to construct comparator 16 have a dynamic range that exceeds the “usable” range of voltages of the received signal. In other words, comparator 16 may receive signals over line 28 having a voltage range that represent only a small portion of the dynamic range of the comparator 16. If one were to simply adjust the threshold signal without regard to

this usable range then it may take an unacceptably long period of time to find an optimum or at least an acceptable threshold level due to this mismatch in ranges.

To reduce this time period and more rapidly find an acceptable threshold level for the comparator 16, it is preferable to first sweep the dynamic range of the comparator 16 to find the usable range. In other words, it is generally preferable to search for the usable range before adjusting the comparator 16 threshold to reduce BER. In this way, the threshold adjustments for receiver circuit tuning may be limited to this usable range or at least have a good starting point. In either case, an optimum or near-optimum threshold value may be found much more rapidly. This usable range search may be skipped or eliminated, if for example, the mismatch between dynamic and usable ranges is not so great. Furthermore, the search may be limited to range centered around a pre-configured, known or estimated decision threshold value to speed the searching process.

Fig. 5 illustrates one method 100 of searching the dynamic range for the usable range. This method 100 may be performed by any of the receiver circuits 22, 23, or 24 described above. Furthermore, this method 100 may be performed during a factory calibration set-up procedure, during a field calibration or at any time before live traffic will be carried. As will be recognized by those skilled in the art, the steps in the illustrated flow charts may be carried out by firmware embedded in the microprocessor 38, software stored in a memory device in or associated with the microprocessor 38 or a combination thereof.

As shown in Fig. 5, the searching method 100 may select a starting point and set the initial decision threshold (110). This may be accomplished by choosing a random starting point, a starting point at one end of the range, a known or configured value, or a point in the middle. In any event, the microprocessor circuit 38 generates a control signal that is used (e.g. via DAC 42)

to send an initial decision threshold signal to the comparator 16. A delay (115) may then be introduced to, for example, permit the system to stabilize.

The searching method 100 shown in Fig. 5 continues by determining if valid bits are being received (120). In other words, the method determines if the decision threshold is at a level sufficient that valid bits are being received. The determination of whether valid bits are being received generally varies with the type of error coding method utilized. In the case of FEC, the bits may be deemed valid when the FEC OOF (out of frame) is false and the bits may be deemed invalid when this condition is true. In other words, the signal may be deemed valid when the FEC decoder in the error correction and detection circuit 20 can synchronize and recognize framing of the incoming signal.

As an alternative to using FEC OOF to determine whether the bits are valid in step 120 it is also possible to use SONET or SDH valid frame detection. While this is a possibility it is not preferred because the FEC frame is more sensitive than the SONET or SDH frames. Of course, coding algorithms other than FEC can be used to not only determine bit errors but also to determine whether the bits are valid. In other words, "valid" could be determined differently depending upon which coding method is used.

If valid bits are being received, then the method stops searching (190) and the microprocessor 38 can utilize the threshold signal level(s) associated with the valid bit(s) as a starting point for tuning the threshold to a more optimum value. In other words, the searching 100 algorithm gets the receiver into the ballpark so that the decision threshold may be tuned more quickly by the tuning algorithm (e.g. 200, 201, 300, 301 discussed below).

If no valid bits are being received, then the microprocessor 38 adjusts the decision threshold (125). A decision (130) is then made as to whether the decision threshold is out of

range (130). For example, has the maximum or minimum DAC 42 count value been exceeded or does the potentiometer 43 have any adjustment left or has the search exceeded a pre-configured subset of the dynamic range centered. If the answer is yes, then the decision threshold must be adjusted to bring it back into range (e.g. changing the direction of adjustment or changing the starting point for adjustment). If not out of range, then another delay (135) may be introduced to permit the system to stabilize. The method then loops back to determine if valid bits are being received with this new threshold level (120).

The searching method 100 illustrated in Fig. 5 may also be modified to determine the range of decision thresholds in which valid bits are received instead of finding a single decision threshold value. In this way, the tuning of the decision threshold may be limited to this range and/or the system may be able to pick a better initial decision threshold (e.g. the middle of the range).

The range referred to in the decision (130) may be the entire dynamic range of the adjustment device (e.g. DAC 42) or it may comprise a subset of that range (e.g. +/- X counts centered about a configured value). It is generally preferred to use a subset of the entire dynamic range where the subset is centered about a configured or preset value so that the searching method takes a shorter amount of time.

FIG. 6 is a flow chart illustrating a decision threshold tuning operation 200 of a receiver consistent with the invention. As will be recognized by those skilled in the art, the steps in the illustrated flow chart may be carried out by firmware embedded in the microprocessor 38, software stored in a memory device in or associated with the control circuit 22, or a combination thereof.



As show in Fig. 6, decision threshold tuning 200 may be a single non-repetitive event. In other words, the invention contemplates a single decision threshold adjustment and does not necessarily perform dynamic tuning in which a series of decision threshold adjustments are made.

5 After starting (202) the tuning process, the method inputs (205) the number of corrected "1"s and "0"s. As described above, the error detection & correction circuit 20 outputs an error signal on line 36 that includes or otherwise represents the number of corrected "1"s and "0"s corrected in the data stream from comparator 16.

10 The tuning method may then perform a calculation (220) based on this error signal. The preferred method calculates a total percentage error indicator which is a measure of the total percentage success of the comparator 16 in accurately deciding between "1"s and "0"s. The percentage error indicator preferably includes a total number of corrected bits so as to normalize the value. In other words, the total percentage error indicator preferably measures the percentage success or failure of the comparator 16 to make binary decisions where the percentage is preferably in relation to the total number of errors (or corrected bits). The most preferred form of this calculation applies the following equation:

$$Indicator = \frac{|(Ones - Zeroes)|}{|(Ones + Zeroes)|},$$

where Indicator = total percentage error indicator,

Ones = the number of corrected "1"s in the output data signal, and

20 Zeroes = the number of corrected "0"s in the output data signal.

The total percentage error indicator may be used in a variety of fashions to arrive at an updated decision threshold signal. A direct calculation of the threshold signal value may be made based on the total percentage error indicator. The preferred embodiment, however, utilizes

the total percentage error indicator to determine the amount of change applied to the current decision threshold value.

In other words, the total percentage error indicator is preferably used to determine how much the decision threshold should be altered. A large total percentage error indicator means that the decision threshold is “lopsided” or skewed too far towards either the “1”s or “0”s and should be rapidly changed. A small total percentage error indicator means that the decision threshold is close to being ideal and that smaller changes should be made to the decision threshold. In this way, the invention may rapidly arrive at a decision threshold value without overshooting and reduce the BER.

One way of formalizing this concept is to mathematically state the relationship between the stepsize (the amount that the decision threshold should be changed), the Indicator, and the Range as follows:

$$\text{stepsize amount} = \text{Indicator} * \text{Range},$$

where

Indicator = total percentage error indicator, and

Range = the range of stepsizes (e.g. the difference between the maximum stepsize and the minimum stepsize).

While this equation form is best stated for receiver 1 shown in Fig. 2 where a DAC 42 is used (points or counts relate to the stepsize amount) the concepts apply equally to the potentiometer embodiment (Fig. 3), the pulse-width modulator embodiment (Fig. 4), or other constructions of a receiver capable of changing the decision threshold. In general, the term “stepsize amount” refers to any change or alteration (either directly or indirectly) of the decision threshold value. A large “stepsize amount” infers a large alteration in the decision threshold and

does not necessarily imply discrete values.

Fig. 10 is an example showing sample values for the number of corrected "1"s, "0"s, total errors and the total preferred percentage error indicator (Diff/Total). At the top of the chart one can see that the receiver is quite out-of-tune: a large total number of errors are being corrected indicating a very out-of-tune receiver. Significantly, there is a large difference between the number of corrected "1"s and the number of corrected "0"s with the number of corrected "1"s far exceeding the number of corrected "0"s. The invention recognizes this difference by calculating a total percentage error indicator (Diff/Total) that is close to unity thereby indicating a large change (large stepsize amount) in the decision threshold is needed to reduce the BER.

In contrast, the bottom of the Fig. 10 table shows a receiver having an optimal or nearly-optimal decision threshold tuning: the number of corrected "1"s nearly equals the number of corrected "0"s and the total number of errors is substantially reduced compared with the top of the chart.

Fig. 9 is a graph of the preferred total percentage error indicator (Diff/Total) as a function of DAC counts (related to the decision threshold value). Fig. 9 plots the values shown in the table of Fig. 10. Both Fig. 9 and Fig. 10 are proof of concept illustrations showing that the total percentage error indicator serves as an excellent basis for changing the decision threshold. As shown therein, a large indicator value (near unity) corresponds quite nicely with a highly out-of-tune decision threshold. Likewise, a small indicator value (near zero) corresponds quite nicely with a relatively in-tune receiver where the number of corrected "1"s is nearly equal to the number of corrected "0"s meaning that the decision threshold is close to optimum. While errors are still observed the receiver is not to blame and is making accurate decisions between "1"s and "0"s.

Figs. 9 and 10 do not show the preferred receiver operation in which the stepsize of decision threshold adjustment is changed according to the size of the total percentage error indicator. Instead, the DAC count (related to the decision threshold value) is changed by increments of 2 in order to show that the total percentage error indicator is an excellent basis for changing the decision threshold.

Fig. 7 illustrates the preferred method of dynamically tuning the decision threshold. The dynamic tuning of Fig. 7 shares many steps with the one-shot tuning of Fig. 6.

In general, the dynamic tuning method (preferred over the one-shot tuning) iteratively adjusts the decision threshold. Certain limits are preferably placed on the adjustment such as setting the stepsize to a minimum amount when the number of corrected errors or the indicator are less than certain values. The preferred method also sets the stepsize to zero when the number of corrected ones equal the number of corrected zeros.

These preferred additions to the dynamic threshold tuning may be performed using the flowchart of Fig. 7. As shown therein, after starting (202) the dynamic tuning method 201 the method inputs (205) the number of corrected "1"s and "0"s. As described above, the error detection & correction circuit 20 outputs an error signal on line 36 that includes or otherwise represents the number of corrected "1"s and "0"s corrected in the data stream from comparator 16. The input (205) process may read the number of corrected "1"s and "0"s for a certain time period such a few seconds to gather a sufficient data set to make informed threshold tuning decisions.

The dynamic tuning method 201 then decides (210) whether an acceptable decision threshold value has been reached. This may be done by determining if the number of corrected

“1”s equals the number of corrected “0”s (Ones = Zeros). If so, then the stepsize is set (260) to zero meaning that no change will be made to the decision threshold value in this iteration.

If an acceptable decision threshold value has not been reached, then the method determines (215) if the decision threshold value is close to being acceptable. This may be done by comparing the total number of errors (e.g. Ones + Zeros) with a threshold value. If the total number of errors is below this threshold then the stepsize is set (250) to a minimum value. In other words, only a minimal adjustment should be made to the decision threshold value to prevent overshoot of the acceptable value.

If the total number of errors exceeds the threshold value then the method proceeds by determining an appropriate stepsize amount. First, the total percentage error indicator is calculated (220) to measure the percentage success or failure of the comparator 16 to make binary decisions where the percentage is preferably in relation to the total number of errors (or corrected bits). The most preferred form of this calculation applies the following equation:

$$Indicator = \frac{|(Ones - Zeroes)|}{(Ones + Zeroes)},$$

where Indicator = total percentage error indicator,

Ones = the number of corrected “1”s in the output data signal, and

Zeroes = the number of corrected “0”s in the output data signal.

The invention may then decide whether to make a minimum adjustment to the decision threshold value or whether a larger adjustment is appropriate. This may be done by deciding (225) whether the indicator exceeds a threshold value. If not, then the method sets (250) the stepsize to a minimum value. If yes, then a larger adjustment is appropriate.

The threshold values utilized by the invention vary depending upon a variety of factors such as the model and type of hardware utilized to construct the receiver, the optical network,

and the received signal strength and quality.

As with the method of Fig. 6, the dynamic tuning method of Fig. 7 utilizes the total percentage error indicator to determine (230) the amount of change applied to the current decision threshold value. Mathematically this determination (230) may be expressed as follows:

$$\text{stepsize amount} = \text{Indicator} * \text{Range},$$

where

Indicator = total percentage error indicator, and

Range = the range of stepsizes (e.g. the difference between the maximum stepsize and the minimum stepsize).

Again, while this equation form is best stated for receiver 1 shown in Fig. 2 where a DAC 42 is used (points or counts relate to the stepsize amount) the concepts apply equally to the potentiometer embodiment (Fig. 3), the pulse-width modulator embodiment (Fig. 4), or other constructions of a receiver capable of changing the decision threshold. In general, the term “stepsize amount” refers to any change or alteration (either directly or indirectly) of the decision threshold value. A large stepsize amount infers a large alteration in the decision threshold.

After determining (230) the stepsize amount, the invention may then proceed to actually change (295) or otherwise adjust the decision threshold by the stepsize amount. The microprocessor 38 may perform this adjustment by adjusting the DAC count (Fig. 1), the potentiometer (Fig. 2), or the pulse-width modulated signal (Fig. 3) or by effecting any other change of the decision threshold value of another receiver design consistent with the concepts of the invention.

The direction of change (+/-) may be inferred by the relative number of corrected “1”s and “0”s. For example, given that there is a direct relationship with decision threshold, and

number of corrected "1"s , if the number of corrected "1"s exceeds the number of "0"s then the decision threshold is too high and must be reduced . Likewise, if the number of corrected "0"s exceeds the number of "1"s then the decision threshold is too low and must be increased. Of course, other ways of inferring the stepsize sign may be used and still be consistent with the concepts of the invention.

After adjusting (295) the decision threshold, the method 201 then loops back to the input (205) step. Iterations of the method 201 may continue in the fashion described above to continuously and dynamically modify the comparator decision threshold to reduce the BER for the received data.

Fig. 8a illustrates another method of dynamically tuning the decision threshold based on a different indicator (a relative percentage error indicator as opposed to the total percentage error indicator described above). The dynamic tuning of Fig. 8a shares many steps with the one-shot tuning of Fig. 6 and the dynamic tuning of Fig. 7. Therefore, detailed explanations of shared steps will not be repeated here.

As shown in Fig. 8a, the alternative decision threshold tuning method 300 inputs (205) Ones and Zeros after starting (202) the tuning process. Then, a relative percentage error indicator is calculated (305). In this alternative, the relative percentage error indicator is calculated as follows:

Indicator = Ones/Zeros or Zeros/Ones depending upon which is greater than 1.

In other words:

Indicator = Ones/Zeros when  $\text{Ones/Zeros} \geq 1$  and

Indicator = Zeros/Ones when  $\text{Zeros/Ones} \geq 1$

The tuning method 300 then decides (310) whether the Indicator exceeds a Ratio Threshold. If yes, then another decision (320) is made in which the absolute value of Ones – Zeros is tested against another Threshold (e.g. if  $|Ones - Zeros| > SecondThreshold$ , then the method sets (330) the stepsize to a maximum value. In other words, there is large difference between the number of corrected Ones and Zeros which indicates that the decision threshold is not close to an optimal value and should be rapidly changed (e.g. by setting the stepsize to a maximum value). Otherwise ( $|Ones - Zeros| \leq SecondThreshold$ ), the stepsize is set to a minimum value (the decision threshold is close to optimum and should be changed by small increments to prevent overshoot).

After determining the stepsize (330 or 350), the method may then adjust (295) the decision threshold by the stepsize in the appropriate direction as described in more detail above.

Fig. 8b illustrates another method (301) of dynamically tuning the decision threshold based on a relative percentage error indicator. The dynamic tuning of Fig. 8b shares many steps with tuning illustrated in Fig. 8a, 7 and 6. Therefore, detailed explanations of shared steps will not be repeated here.

An additional feature of the tuning method 301 illustrated in Fig. 8b is the no decision threshold adjustment path. Specifically, a decision (345) may be made as to whether the number of corrected Ones equals the number of corrected Zeros. If so, then it may be presumed that an acceptable decision threshold has been reached since there is an even split between corrected Ones and Zeros. Fig. 8b illustrates this no adjustment path by looping back to the input (205) step after determining that the number of corrected Ones equals the number of corrected Zeros. A similar no adjustment path may be added to the tuning method 300 illustrated in Fig. 8a.



The Fig. 8b tuning method 301 also uses a Total Count value (as opposed to the absolute value of Ones – Zeros) to further determine the stepsize value. Specifically, a decision (322) is made in which the Total Count (total number of corrected Ones and corrected Zeros) is tested against another Threshold (e.g. if *TotalCount* > *ThirdThreshold* , then the method sets (330) the stepsize to a maximum value. In other words, there a large number of errors need to corrected then this indicates that the decision threshold is not close to an optimal value and should be rapidly changed (e.g. by setting the stepsize to a maximum value). Otherwise (*TotalCount* ≤ *ThirdThreshold* ), the stepsize is set to a minimum value (the decision threshold is close to optimum and should be changed by small increments to prevent overshoot).

It is to be understood that the illustrated flow charts are provided by way of explanation, not of limitation. Alternative methods adjusting the comparator decision threshold in manner consistent with the invention will be apparent to those skilled in the art.

There is thus provided an optical receiver configuration that dynamically adjusts the receiver decision threshold to achieve and maintain an optimized system BER. Consistent with the invention, the receiver includes a control circuit (e.g. 22, 23 or 24) in a feedback loop. The control circuit adjusts a decision threshold to a comparator based on error rate information derived from the data stream and, preferably, the comparator decision threshold is adjusted at a rate that varies according to the indicator.

Generally speaking the inventive systems and methods disclosed herein are independent of the modulation format. In other words, the invention is not restricted to any specific modulation format (e.g. OOK, RZ, NRZ, soliton, QAM and QPSK) and may be applied to any known or future-developed modulation format.

The inventive concepts are quite useful for rapidly and accurately adapting the decision

threshold to reduce the number of errors. A variety of factors in the optical network may influence what decision threshold value reduces errors including factors such as cross phase modulation, four wave mixing, self phase modulation, OSNR changes, Raman crosstalk, stimulated Brillion scattering, and jitter. Moreover, these factors are influenced by fiber type, weather the fiber is in, number of channels, length of spans, types of amplifiers, launch power into fiber from transmitter and a variety of other effects in the fiber itself. The invention compensates for all of these factors and influences by intelligently adjusting the decision threshold as described above in detail.

The embodiments that have been described herein, however, are but some of the several which utilize this invention and are set forth here by way of illustration but not of limitation. It is obvious that many other embodiments, which will be readily apparent to those skilled in the art, may be made without departing materially from the spirit and scope of the invention as defined in the appended claims.